



Grupp Group	3	PV 445, P 210				VOLVO
Sida Page	18	Utgåva Issue	2	Generator, generatorupphängning, laddningsregulator	Generator, generator mountings, charging relay	Reservdelskatalog Parts catalogue

Pos Fig.	Antal Qty.								Benämning	Description	Det. nr Part No.	Anmärkning Notes
	72571	72941	77904	76837	233630	233576	238767	238769				
1	1								Generator, kmp	Generator, cpl	72571-3	1)
		1							Generator, kmp	Generator, cpl	72941-8	2)
				1					. Detaljer, se sida 22	. Components see page 22		
					1				Generator, kmp	Generator, cpl	77904-1	3)
						1			Generator, kmp	Generator cpl	76837-4	4)
									. Detaljer, se sida 26	. Components, see page 26		
							1		Generator, kmp	Generator, cpl	233630-3	5)
								1	Generator, kmp	Generator, cpl	233576-8	6)
								1	Generator, kmp	Generator, cpl	238767-8	7)
								1	Generator, kmp	Generator, cpl	238769-4	8)
									. Detaljer, se sida 30	. Components, see page 30		
1	1								Konsol	Bracket	403268-6	
				1					Konsol	Bracket	403442-7	9)
					1				Konsol	Bracket	403572-1	9, 10)
						1			Konsol	Bracket	403748-7	11)
							1		Konsol	Bracket	403880-8	12)
2					1	1	1	1	Konsol	Bracket	403891-5	
3			1	1					Remskiva	Pulley	403443-5	
4	2								Skruv	Bolt	902282-3	1 = 30
		2	2						Skruv	Bolt	104505-3	1 = 25
				2					Skruv	Bolt	902307-8	1 = 35
5				2	2	2	2	2	Skruv	Bolt	921842-1	1 = 25

- Auto-Lite: GDZ - 4821 A
B4B t o m motor nr 12096. Ersättes av 1 st generator 72941-8, 1 st spännjärn 403381-7 och 1 st bricka 11962-8.
- Auto-Lite: GDZ - 60016
B4B motor nr 12097-43099.
- Bosch: LJ/GJM 160/6 - 1500 R 7.
B4B motor nr 43100-73048, 74630-75219. Ersättes av 1 st generator 76837-4, 6 st bussning 403877-4, 6 st bricka 403878-2, 3 st hylsa 403879-0, 1 st konsol 403880-8 samt 3 st skruv 902282-3.
- Bosch: LJ/GJM 160/6 - 1800 R 10.
B4B fr o m motor nr 75220 samt nr 73049-74629, B14A.
- Bosch: LJ/GG 200/6/2300 R 7.
B16A t o m motor nr 100122.
B16B utom motor nr 114460-114501, 114587-114877 115145-115887.
- Bosch: LJ/GG 200/6/2300 R 6.
B16A motor 100123-187188.
Ersättes av generator 238767-8.
- Bosch: LJ/GG 200/6/2300 A R 6 mr.
B16A fr o m motor nr 187189.
Detaljer se katalog P 120 (B16) Grupp 3.
- Bosch: LJ/GG 200/6/2300 AR 7 mr.
B16B motor nr 114460-114501, 114587-114877, 115145-115887.
Detaljer se katalog P 120 (B16) Grupp 3.
- Ersättes av 1 st sats 54894-1.
- B4B motor nr 73049-74629 och 75220-139165.
- B14A t o m motor nr 1826.
- B4B fr o m motor nr 139166.
B14A fr o m motor nr 1827.

- Auto-Lite: GDZ - 4821 A
B4B up to engine No 12096. Replaced by 1 generator 72941-8, 1 tensioner 403381-7 and 1 washer 11962-8.
- Auto-Lite: GDZ - 60016
B4B engines Nos 12097 - 43099.
- Bosch: LJ/GJM 160/6 - 1500 R 7
B4B engines Nos 43100-73048, 74630-75219. Replaced by 1 generator 76837-4, 6 bushings 403877-4, 6 washers 403878-2, 3 sleeves 403879-0, 1 bracket 403880-8 and 3 bolts 902282-3.
- Bosch: LJ/GJM 160/6 - 1800 R 10
B4B w e f engine No 75220 and Nos 73049 - 74629 B14A.
- Bosch: LJ/GG 200/6/2300 R 7.
B16A up to engine No 100122.
B16B except engines Nos 114460-114501, 114587-114877 115145-115887.
- Bosch: LJ/GG 200/6/2300 R 6
B16A engines Nos 100123-187188
Replaced by generator 238767-8.
- Bosch: LJ/GG 200/6/2300 AR 6 mr
B16A w e f engine No 187189
Components, see P 120 (B16) Catalogue, Group 3.
- Bosch: LJ/GG 200/6/2300 AR 7 mr
B16B engines Nos 114460-114501, 114587-114877, 115145-115887
Components, see P 120 Parts Catalogue, Group 3.
- Replaced by 1 set 54894-1.
- B4B engines Nos 73049-74629 and 75220-139165.
- B14A up to engine No 1826.
- B4B w e f engine No 139166.
B14A w e f engine No 1827.

Grupp Group		3						PV 445, P 210		VOLVO Reservdelskatalog Parts catalogue		
Sida Page	20	Utgåva Issue		2		Generator, generatorupphängning, laddningsregulator		Generator, generator mountings, charging relay				
Pos Fig.	Antal Qty.								Benämning	Description	Det. nr Part No.	Anmärkning Notes
	72571	72941	77904	76837	233630	233576	238767	238769				
6	2								Mutter	Nut	10592-4	
		2	2						Mutter	Nut	903470-3	
				2					Mutter	Nut	10593-2	
7					2	2	2	2	Mutter	Nut	950367-3	
		2	2						Saxpinne	Cotter pin	907823-9	
8	2	2	2	2	2				Fjäderbricka	Spring washer	906990-7	
9					2	2	2	2	Bricka	Washer	951719-4	
10	3								Skruv	Bolt	902279-9	1 = 19
		3	3	3					Skruv	Bolt	902278-1	1) 1 = 16
11					3	3	8	3	Skruv	Bolt	902282-3	2) 1 = 30
12	3	3	3						Fjäderbricka	Spring washer	906990-7	
13				6	8	8	8	8	Gummibussning	Rubber bushing	403877-4	
14				3					Distanshylsa	Spacer sleeve	403879-0	
				4	4	8	8		Distanshylsa	Spacer sleeve	403894-9	
15				6	8	8	8	8	Bricka	Washer	403878-2	
16				1	1	1	1	1	Låsbricka	Lock washer	403839-4	
17	1								Spännjärn	Tensioner	403347-8	
		1	1	1					Spännjärn	Tensioner	403381-7	
18					1	1	1	1	Spännjärn	Tensioner	418009-7	
19	1								Skruv	Bolt	902278-1	1 = 16
		1	1	1					Skruv	Bolt	902283-1	1 = 35
20					1	1	1	1	Skruv	Bolt	905298-5	105208
21	1								Fjäderbricka	Spring washer	906990-7	
		1	1	1					Packning	Gasket	11992-5	
22					2				Gummibussning	Rubber bushing	403877-4	
23				1	1	1	1	1	Distanshylsa	Spacer sleeve	403894-9	
24					2	2	2	2	Bricka	Washer	403878-2	
25					1	1	1	1	Låsbricka	Lock washer	955949-3	17835
26	1	1	1	1					Skruv	Bolt	101925-6	1 = 17
27					1	1	1	1	Skruv	Bolt	955525-1	1 = 25 105217
28					1	1	1	1	Mutter	Nut	955826-3	191081
29	1								Bricka	Washer	906825-5	
30	1								Fjäderbricka	Spring washer	906990-7	
31		1	1	1	1	1	1	1	Bricka	Washer	120096-3	D = 18
32					1	1	1	1	Bricka	Washer	191172-6	D = 20
33	1	1	1	1	1	1	1	1	Fjäderbricka	Spring washer	955921-2	18874
34	1	1	1	1					Drivrem	Drive belt	403109-2	
					1	1	1	1	Drivrem	Drive belt	951684-0	
	1	1							Laddningsregulator	Charging relay	72942-6	3,4) Auto-Lite: 6003
				1					Laddningsregulator	Charging relay	77882-9	1, 3, 4, 6)
				1	1				Laddningsregulator	Charging relay	76811-9	2, 3, 5, 7)

1. Tid utf
2. Sen utf
3. B4B.
4. Ersättes av 1 st laddningsregulator 76811 och 3 st skruv 190364.
5. B14A.
6. Bosch: RS/JA 160/6/30
7. Bosch: RS/JA 160/6/16

1. Early prod.
2. Late prod.
3. B4B.
4. Replaced by 1 charging relay 76811 and 3 bolts 190364.
5. B14A.
6. Bosch: RS/JA 160/6/30.
7. Bosch: RS/JA 160/6/16.

Grupp Group		3		PV 445, P 210				VOLVO Reservdelskatalog Parts catalogue				
Sida Page	21a	Utgåva Issue	1		Generator, generatorupphängning, laddningsregulator		Generator, generator mountings, charging relay					
Pos Fig.	Antal Qty.								Benämning	Description	Det. nr Part No.	Anmärkning Notes
	72571	72941	77904	76837	233630	233576	238767	238769				
35					1	1	1	1	Laddningsregulator, kompl	Charging relay, cpl	233506-5	1)
36					2	2	2	2	. Skruv Screw	115105-9	
37					2	2	2	2	. Fjäderbricka Spring water	906985-7	
38					1	1	1	1	. Skruv Screw	6605147-5	
39					1	1	1	1	. Lösbricka Lock washer	17840-0	
40					3	3	3	3	. Gummibussning Rubber bushing	233566-9	
	3	3							Skruv	Screw	955271-2	1 = 16 -105204-
			4						Skruv	Screw	115078-8	2) 1 = 12
41		3	3	3	3	3	3	3	Skruv	Screw	190364-0	3) 1 = 16
	3	3							Fjäderbricka	Spring washer	906987-3	
			4						Fjäderbricka	Spring washer	906985-7	

1. Bosch: RS/JA 200/6
B16A, B16B.
2. Tid utf
3. Sen utf

1. Bosch: RS/JA 200/6
B16A, B16B.
2. Early prod
3. Late prod